EXPLODED VIEW

GRINDER DOSER
ROBUR ELECTRONIC


ESROELE01.00 07/2008

MAZZER®

MAZZER LUIGI s.r.l.
VIA MOGLIANESE, 113
30030 GARDIGIANO DI SCORZE' (VE)
ITALIA
TEL. +39 041 5830200 r.a. - FAX +39 041 5830060
E-mail: mazzer@mazzer.com - http: www.mazzer.com

N.	DESCRIPTION	CODE	Q.	NOTES
1	Hopper cover	S000COD01	1	
2	Magnet with ring	S00SCAC01	-	Optional
3	Label "Caution Hopper"	S000ETA15	1	110V/60Hz versions 100V/50-60Hz versions 220V/60Hz versions
4	Hopper Major/Robur	S00SCAE03	1	
5	Robur collar locking slide	S000SEB02	1	
6	Safety switch	S000INR01	1	
7	Connection cable for fan	S000CON01	1	
8	Fan 80x80 - wired	S00SVEB02	1	
9	Frame for fan 80x80	S000SUV02	1	
10	Filter for fan 80x80	S000FIV02	1	
11	"Mazzer 4M" plate	S000TAA02	1	
12	Body for Robur electronic	SRO0CAA12	1	
13	Two pole rotative switch	S000INA09	1	
14	Switch plate O / I	-	1	
15	Rotative switch knob	-	1	
16	"Danger" plate	S000TAA21	1	110V/60Hz vers. 100V/50-60Hz vers.
17	Motor label	-	1	
18	Drip tray	SMJ0PIB02	1	
19a	Pilot light 230/400V - green	S000LAA06	1	220-240V/50Hz versions 220V/60Hz versions
19b	Pilot light 110V UL - red	S000LAA07	1	110V/60Hz versions 100V/50-60Hz versions
20	Fork for electronic RO-RL-MJ	S000FOB14	1	
21	Motor cover for Robur electronic	SRO0FRA00	1	
22	Cable locking 40-80-20 black	S000PAB05	1	
23	Adhesive membrane with display	S000MEM04	1	
24	Push button holder lid with display	S000COG02	1	
25	Gasket push button holder lid	S000GUA04	1	
26	Card for push button with display	S000SPU03	1	
27	Bottom for push button lid	S000FOC00	1	
28	Coffee outlet guard	S000PRB02	1	
29	Label "Danger"	S000ETA14	2	110V/60Hz versions 100V/50-60Hz versions 220V/60Hz versions
30	Funnel H180	S000IMB02	1	
31	Grid	S000RET03	1	
32	Gasket Aer-Stop	S000GUA01	1	
33	Upper gasket	S000GUA03	1	
34	Label: Motor rotation	S000ETA00	1	
35	Support for filter holder	S00SSUP01	1	
36a	Hand tamper double diam. D. 52.5 / 57.8	S000PRD02	1	D. 52.5 / 57.8
36b	Hand tamper double diam. D. 52.5 / 54.5	S000PRD02	1	D. 52.5 / 54.5
37	Label: Coarse - fine / Adjustment initial position	S000ETA03	1	
38	Coffee grinding adjustment disk - Major	SMJ0GHA04	1	
39	Upper grinding blade holder Robur single phase	SRO0POA03	1	Single phase vers.
40	Grinding adjustment spring	SSJ0MOB01	4	
41	Grinding adjustment disk handle	SSJSPEA04	1	
42	Conical grinding blade set 186C single phase	FMA00186C	1	Single phase vers.
43	Propeller Robur single phase	SRO0ELI00	1	Single phase vers.
44	Lower grinding blade holder Robur	SRO0POA07	1	
45	Ring O.R.- SEAL	S000ANA03	1	
46	Bearing 6202 DDU CM	S000CUA07	2	
47	Grinding tray for Robur	SRO0BAA01	1	
48	Thickness planetary shaft	S000SPB02	1	
49	Key 3x3x30 UNI 6604 A	S0CH30030	1	
50	Planetary shaft	S00SALA04	1	
51	Reduction satellite	S000SAT01	3	
52	Reduction planet	S000PIR02	1	
53	Reduction crown	S000COR01	1	
54	Upper motor cap Robur	SRO0CAB03	1	
55	Bearing 6204 DDU CM	S000CUA04	2	
56	Major cooling fan	SMJ0VEA01	1	
57	Fan fixing clamp	S000FAA01	1	
58	Robur rotor	SRO0ROA02	1	
59a	Robur coiled stator-single phase 220-240V/50Hz	SROSPAE01	1	220-240V/50Hz single phase vers.
59b	Robur coiled stator-single phase 110V/60Hz	SROSPAA08	1	110V/60Hz single phase vers.
59c	Robur coiled stator-single phase 100V/50-60Hz	SROSPAJ00	1	100V/50-60Hz single phase vers.
59d	Robur coiled stator-single phase 220V/60Hz	SROSPAS01	1	220V/60Hz single phase vers.
60	Rotor-motor cup thickness	SRO0SPE00	1	
61	Lower motor cap Robur/Royal	SRL0CAB01	1	
62	A18x8,5 M vibration damping	S000ANV04	3	
63	Motor plate Robur	SRO0PIA01	1	
64	Under terminal board	P000SOT02	-	
65	Nut for cable locking 3213B	S000DAA02	1	

N.	DESCRIPTION	CODE	Q.	NOTES
66	Bottom plate for Robur electronic	SRO0PIE01	1	
67	DD 2015 H support leg	P000PIA04	4	
68	"Ground" plate	S000TAA18	1	
69	"External unipotential clamp" plate	S000TAA19	1	CE versions
70a	Electric cable - "Italy"	S000CAD01	1	
70b	Electric cable - "Europe"	S000CAD04	1	
70c	Electric cable "USA" - SJT 3x16AWG	S000CAD11	1	
70d	Electric cable - "Australia"	S000CAD07	1	
70e	Electric cable - "Great Britain"	S000CAD08	1	
70f	Electric cable - "Israel"	S000CAD10	1	
70g	Electric cable - "Switzerland"	S000CAD06	1	
70h	Electric cable - "China"	S000CAD16	1	
70i	Electric cable - "Argentina"	S000CAD18	1	
70j	Electric cable - "Korea"	S000CAD19	1	
71	Cable locking 3243 flex. LTF11 PG11 black	S000PAB04	1	
72	Cable locking support	S000SUA01	1	
73a	Capacitor 16uF	S000COE03	1	220-230V/50Hz single phase vers. 230-240V/50Hz single phase vers. 220V/60Hz single phase vers. 240V/50Hz single phase vers.
73b	Capacitor 60uF UL	S000COE09	1	100V/50-60Hz single phase vers. 110V/60Hz single phase vers.
74a	Strap RELF 170 black	S000FAS06	1	Capacitor 16uF Capacitor 20uF
74b	Capacitor locking clamp 50	S000GRB04	1	Capacitor 60uF UL Capacitor 80uF UL
75a	Relè "Texas" 2CR4-170	S000DIS02	1	220-230V/50Hz single phase vers.
75b	Relè "Texas" 2CR4-181	S000DIS03	1	230-240V/50Hz single phase vers. 220V/60Hz single phase vers.
75c	Relè "Texas" 2CR4-240	S000DIS06	1	100V/50-60Hz single phase vers. 110V/60Hz single phase vers.
76a	Capacitor 20uF	S000COE04	1	220-230V/50Hz single phase vers. 230-240V/50Hz single phase vers. 240V/50Hz single phase vers.
76b	Capacitor 80uF UL	S000COE10	1	100V/50-60Hz single phase vers. 110V/60Hz single phase vers.
76c	Capacitor 16uF	S000COE03	1	220V/60Hz single phase vers.
77a	Board for double timer 220-240V el. C	S000SCT06	1	220-240V/50Hz vers. 220V/60Hz vers.
77b	Board for double timer 100-115V el. C	S000SCT07	1	110V/60Hz vers. 100V/50-60Hz vers.
78a	Load resistor 220 Kilo-ohm 2 Watt	S000REB01	1	220-240V/50Hz single phase vers. 220V/60Hz single phase vers.
78b	Load resistor 68 Kilo-ohm 2 Watt	S000REB02	1	100V/50-60Hz single phase vers. 110V/60Hz single phase vers.
79	Terminal blocks	P000MOA04	-	
80	Support for motor cover	SRO0SUP02	1	


CAUTION
DANGER
MOTORE